Cable Reference

Audina Hearing Instruments, Inc.

Report generated Nov 18, 2026, 10:11:35 pm

Cable Matrix

Product	Housing	Cable	Connector	Programmer	Notes
nVe 4 / AD	RIC	Gray-4x	Flexstrip CS54 (4-pin)	HI-PRO, EMiniTec (v1)	NOAHlink or EMiniTec2 programmers will only work with special Gray-3x cables.
TransEar 12	BTE	Black-5x	Flexstrip CS54 (4-pin) with Flexstrip "Pyramid" Adapter, or Flexstrip XtendPads (4-pin)	All	
TransEar	BTE	Gray-4x	Flexstrip CS54 (4-pin)	All	
Sparo 2 / 2+ / 2ER / 4 / AD / 12	OTE	Gray-4x	Flexstrip CS54 (4-pin)	All	
Simplex 2P BTE / 2P+	BTE	Gray-4x	None	All	
SU7 / Suite	BTE	Black-5x	None	HI-PRO, FittingLINK 2	Program using Oasis software.
SU7 / Suite	RIC	Black-5x	Flexstrip 8-inch (3-pin)	HI-PRO, FittingLINK 2	Program using Oasis software.
SU7 / Suite	BTE	Black-5x	None	HI-PRO, FittingLINK 2	Program using Oasis software.
Octane 4 / 6 / 12	Super Power	Black-5x	None	All	
MI3 / Mirum	BTE	Black-5x	None	HI-PRO, FittingLINK 2	Program using Oasis software.
MI3 / Mirum	RIC	Black-5x	Flexstrip 8-inch (3-pin)	HI-PRO, FittingLINK 2	Program using Oasis software.
MI3 / Mirum	BTE	Black-5x	None	HI-PRO, FittingLINK 2	Program using Oasis software.
Intuition 4 / 6	BTE	Black-5x	None	All	
Intuition 2 / 2FC / 4 / 4D	BTE	Gray-4x	None	HI-PRO, EMiniTec (v1)	NOAHlink or EMiniTec2 programmers will only work with special Gray-3x cables.
Intuition 2 / 2+ / 2FC / 2FC+ / 2ER / 4 / 4+ / 4D / 4AD / 6 / 12	ITE	Gray-4x	None or Flexstrip CS54 (4-pin)	All	
Intuition (Stock Canal) 2 / 2+ / 2FC / 2FC+ / 2ER / 4 / 4+ / 4D / 4AD / 6 / 12	Stock	Cable Pill 10A Left Cable Pill 10A Right	None	All	Cables are side and battery size specific. Select from: Cable Pill 10A, Cable Pill 13, Cable Pill 312
Intellio	ITE	Gray-4x	None or Flexstrip	All	

			CS54 (4-pin)		
InstaFIT Cue	Stock	Cable Pill 10A Left Cable Pill 10A Right	None	All	Cables are side and battery size specific. Select from: Cable Pill 10A, Cable Pill 13, Cable Pill 312
InstaFIT 2ER / 4+ (without VC)	Stock	Gray-4x	Flexstrip CS54 (4-pin)	All	
InstaFIT 2ER / 4+ (with VC)	Stock	Gray-4x	Battery Door Adapters 10A Pill (Left) 10A Pill (Right)	All	Adapters are side specific.
IRIC 2 / 4 / 6 / 12	RIC	Black-5x	Flexstrip CS54 (4-pin)	All	
IIC Family	IIC	Cable Pill 10A Left Cable Pill 10A Right	None	All	Cables are side and battery size specific. Select from: Cable Pill 10A, Cable Pill 13, Cable Pill 312. Some IIC products may use flexstrips instead, which require using Gray-4x cables instead.
Flx 4 / 6 / 12	OTE	Black-5x	None	All	Flx products manufactured before Sep 2013 require Gray-4x cables. Products starting Sep 2013 (with serial number 13-1256xx or higher) require Black-5x cables.
Flx (1st Gen)	OTE	Gray-4x	None	All	Flx products manufactured before Sep 2013 require Gray-4x cables. Products starting Sep 2013 (with serial number 13-1256xx or higher) require Black-5x cables.
Cue MRIC	RIC	Black-5x	None	All	
Cue	IIC	Cable Pill 10A Left Cable Pill 10A Right	None	All	Cables are side and battery size specific. Select from: Cable Pill 10A, Cable Pill 13, Cable Pill 312
Coral	RIC	Black-5x	Flexstrip 8-inch (3-pin)	HI-PRO, FittingLINK 3, Noahlink Wireless	Program using Oasis nxt software.
Capto	BTE	Black-5x	None	HI-PRO, FittingLINK 3, Noahlink Wireless	Program using Oasis nxt software.

Capto	RIC	Black-5x	Flexstrip 8-inch (3-pin)	HI-PRO, FittingLINK 3, Noahlink Wireless	Program using Oasis nxt software.
Capto	BTE	Black-5x	None	HI-PRO, FittingLINK 3, Noahlink Wireless	Program using Oasis nxt software.
BTE D6P	BTE	Gray-4x	None	All	
BTE D6HP	BTE	Gray-4x	None	All	
BTE 6AD	BTE	Black-5x	Flexstrip CS54 (4-pin) with Flexstrip "Pyramid" Adapter, or Flexstrip XtendPads (4-pin)	All	
BTE 675DP+	BTE	Gray-4x	None	All	
BTE 478P / 478P+	BTE	Gray-4x	None	All	
Arro RIC 2 / 6 / 6AD / 12	RIC	Black-5x	Flexstrip XtendPads (4-pin)	All	Must use Flexstrip XtendPads, not regular Flexstrip CS54.
Arro OTE 2 / 6 / 6AD / 12	OTE	Black-5x	Flexstrip XtendPads (4-pin)	All	Must use Flexstrip XtendPads, not regular Flexstrip CS54.

Cables

Name	Cable	Compatibility	Notes
Gray-4x		Unitron, Phonak, GNResound	Mostly used for custom products.
Black-5x		Siemens, Oticon, Bernafon, PHSI	Mostly used for newer stock products.
Cable Pill 10A Left		None	Cables are side and battery size specific. Select from: Cable Pill 10A, Cable Pill 13, Cable Pill 312.
Cable Pill 10A Right		None	Cables are side and battery size specific. Select from: Cable Pill 10A, Cable Pill 13, Cable Pill

			312.
Gray-3x		None	Use only with NOAHlink or EMiniTec2 programmers reading Intuition BTE's or nVe OTE's.

Connectors

Name	Connector	Notes
Flexstrip CS54 (4-pin)		Not compatible with all products that require flexstrips. Use Flexstrip XtendPads for full compatibility.
Flexstrip XtendPads (4-pin)		Compatible with any product that needs Flexstrip CS54 (4-pin). However, the reverse is not true. Recommended flexstrip for all products.
Flexstrip 8-inch (3-pin)		Only for use with wireless products.
Battery Door 10A Pill Adapter (Left)		Must remove battery door. Adapter is side specific.
Battery Door 10A Pill Adapter (Right)		Must remove battery door. Adapter is side specific.

		

"

Programmers

Name	Programmers	Data Cable
HI-PRO (Classic)		Null-modem serial cable, with USB-serial adapter
HI-PRO (USB)		USB cable
HI-PRO 2 (USB)		USB cable
NOAHlink		Wireless Bluetooth adapter (no cable)
Noahlink Wireless		USB cable
EMiniTec (v1)		

		USB cable
EMiniTec 2		USB cable
FittingLINK 2		Wireless Bluetooth adapter (no cable)
FittingLINK 3		Device directly plugs into USB port.

Housings

Name	Type	Housing	Connection	Cable	Connector	Notes
BTE Classic	BTE			Gray-4x	None	Use socket.
BTE Euro	BTE			Black-5x	Flexstrip CS54 (4-pin) with Flexstrip "Pyramid" Adapter, or Flexstrip XtendPads (4-pin)	
BTE Int	BTE			Gray-4x	None	Use socket. NOAHlink or EMiniTec2

						programmers will only work with special Gray-3x cables.
BTE Intuition	BTE			Black-5x	None	Use socket inside battery compartment.
BTE (Super Power)	BTE (Super Power)			Black-5x	None	Use socket inside battery compartment.
BTE Nano	BTE			Black-5x	None	
BTE PowerBTE	BTE			Black-5x	None	
InstaFIT (with VC)	Stock			Gray-4x	Battery Door 10A Pill Adapter (Left) Battery Door 10A Pill Adapter (Right)	Must remove battery door. Adapter is side specific.
InstaFIT (without VC)	Stock			Gray-4x	Flexstrip CS54 (4-pin), or Flexstrip XtendPads (4-pin)	Use flexstrip.

InstaFIT (IIC)	Stock			Cable Pill 10A	None	Must remove battery door. Cables are side and battery size specific. Select from: Cable Pill 10A, Cable Pill 13, Cable Pill 312.
ITE (Custom)	ITE (Custom)			Gray-4x	None, or Flexstrip CS54 (4-pin) / Flexstrip XtendPads (4-pin)	Use socket or flexstrip, depending how it was ordered.
IIC Beige (Custom)	IIC (Custom)			Gray-4x	None, or Flexstrip CS54 (4-pin) / Flexstrip XtendPads (4-pin)	Use socket or flexstrip, depending how it was ordered.
IIC Black (Custom)	IIC (Custom)			Cable Pill 10A	None	Must remove battery door. Cables are side and battery size specific. Select from: Cable Pill 10A, Cable Pill 13, Cable Pill 312.
MRIC	RIC			Black-5x	Flexstrip CS54 (4-pin)	Slightly open battery door while inserting flexstrip, then completely close the door.
OTE v1	OTE			Gray-4x	Flexstrip CS54 (4-pin), or Flexstrip XtendPads (4-pin)	Insert flexstrip in slit below push-button in battery door, and completely close the door.
OTE v2	OTE			Black-5x	Flexstrip CS54 (4-pin), or Flexstrip XtendPads (4-pin)	Use socket. Products manufactured before Sep 2013 require Gray-4x cables. Products starting Sep 2013 (with serial number 13-1256xx or

						higher) require Black-5x cables.
OTE v4	OTE			Black-5x	Flexstrip XtendPads (4-pin)	Must use Flexstrip XtendPads (4-pin) only. Slightly open battery door while inserting flexstrip, then completely close the door.
RIC v1	RIC			Gray-4x	Flexstrip CS54 (4-pin), or Flexstrip XtendPads (4-pin)	Distinguishing characteristic: bump on each side. Slightly open battery door while inserting flexstrip, then completely close the door. NOAHlink or EMiniTec2 programmers will only work with special Gray-3x cables.
RIC v3	RIC			Black-5x	Flexstrip CS54 (4-pin), or Flexstrip XtendPads (4-pin)	Distinguishing characteristic: depression on each side. Slightly open battery door while inserting flexstrip, then completely close the door.
RIC v4	RIC			Black-5x	Flexstrip XtendPads (4-pin)	Must use Flexstrip XtendPads (4-pin) only. Slightly open battery door while inserting flexstrip, then completely close the door.
RIC Pico	RIC			Black-5x	None	
RIC Mini T	RIC			Black-5x	None	

Stock Canal	Stock			Cable Pill 10A	None	Must remove battery door. Cables are side and battery size specific. Select from: Cable Pill 10A, Cable Pill 13, Cable Pill 312.